
Resonant Frequency Doubler for CW single-frequency lasers, model FD-SF-07

Tekhnoscan presents new resonant frequency doubler, model FD-SF-07, with Smart Auto-Relock function for CW single-frequency lasers (Ti:Sapphire, Dye, Ar, DPSS etc.) that opens a **new possibilities for more efficient laser wavelength conversion** in the visible and near IR ranges into the blue and UV domains. Optimised resonator of FD-SF-07 in combination with high-quality mirrors ensures relatively **high level of output second-harmonic power.** Pumped with 1 W fundamental radiation power the doubler outputs: more than 250 mW within the 350-475 nm range (for 700-950-nm input), > 200 mW within the 275-350 nm range (for 550-700-nm input), and > 150 mW within the 244-275 nm range (for 488-550-nm input).



The Smart Auto-Relock function allows FD-SF-07 doubler to smoothly track considerable changes in the frequency of the input radiation, thus the range of smooth second-harmonic frequency scanning **may cover dozens of GHz**, being only limited by the spectral acceptance of the non-linear crystal. The FD-SF-07 doubler is notable for its low acoustic noise and sensitivity to vibrations, as well as for the **simplicity of tuning and ease of use**. Super-stable and compact ring cavity combined with ultra-fast two-stage system that locks the cavity to the frequency of the input radiation by the Hansch-Couillaud method are a guarantee for **high stability of the output power** of the second harmonics even for lasers without a frequency stabilisation. In combination with the Smart Auto-Relock function the electronic control system of FD-SF-07 ensures **fail-safe operation** of the doubler in a variety of experimental conditions.

Tekhnoscan JSC

Sirenevaia 37, k. 141, Novosibirsk, 630058, Russia Tel./fax: +7-(383)-339-72-24, email: service@tekhnoscan.com

Representative in USA: Del Mar Photonics, Inc.

4119 Twilight Ridge, San Diego, CA 92130

Tel: (858) 876-3133, fax: (858) 630-2376, e-mail: sales@dmphotonics.com



- Improved doubling efficiency up to 40% at the input radiation power 1 W
- Power-enhancement factor up to 130
- Rigid and stable, easily aligned cavity with vibration isolation



- Fast two-stage system of locking the cavity to the frequency of input radiation
- Possibility of efficient operation with lasers without frequency stabilisation
- Solid ultra-stable performance even under conditions of considerable external acoustic perturbations and vibrations
- Thermo-stabilised nonlinear crystal



- A separate control photodetector included into the standard set of the electronic unit
- © Convenient express-access to the alignment of the nonlinear crystal through a special easily removable lid